

PROFESSIONAL

FBPS-2

STEREO BATTERY POWERED 48V PHANTOM POWER SUPPLY

The FBPS-2 utilizes a high frequency switch-mode power supply which converts 18 vdc to a highly regulated output to drive microphones requiring 12 vdc to 48 vdc. It has isolation from input to output to block any DC leakage. The FBPS-2 is specifically designed for use in remote recording or when 120 vac is not available. It is housed in an indestructible metal chassis using only the finest audiophile-quality components. Low battery and battery on led's are also included. For any situation requiring isolated DC phantom power the FBPS-2 and is always the right choice for the job.

- ❑ Works with any microphone requiring 12 vdc to 48 vdc.
- ❑ Delivers up to 10 ma per channel
- ❑ Exceptionally Low Noise
- ❑ Low Distortion
- ❑ Excellent Dynamic Response
- ❑ Isolated Outputs Protect Other Equipment
- ❑ Uses only 1% metal film resistors
- ❑ Made with only the finest audio-file components
- ❑ On / Off Power Switch
- ❑ Power On led Indicator
- ❑ Low Battery led Indicator
- ❑ Long Battery Life, typical battery life of 200 hrs.
- ❑ Indestructible packaging
- ❑ Removable Battery Clip
- ❑ All Markings On Top of Unit
- ❑ Full Three Year Warranty
- ❑ Homegrown in California, USA

FBPS-2 SPECIFICATIONS	
Frequency Response +0, -.01dB	20Hz-20kHz
Bandwidth +0dB, -3dB	2Hz-200kHz
Signal to Noise	-120 Db
Distortion	0.001%
Input Connectors	3 PIN XLR
Output Connectors	3 PIN XLR
Output Phase	Pin 2 Pos., Pin 3-, Pin 1 Gnd.
DC Blocking	100% from input to output
Channels	TWO
Height	1.73"
Width	5.1"
Depth	3.5"
Weight	1 Lb.
Power Requirements	2-9V BATTERIES
Battery Life (Typical)	150 Hrs.
Comes With Optional Belt Clip	



AUDIO ACCESSORIES

FatPro
TECHNOLOGIES

PHONE : (8 7 7)- 4 5 4 -4 4 0 4

FAX : (9 1 6)- 9 8 7 -6 3 3 1

e- m a i l : info@fatpro.com

website: www.fatpro.com